

**zBoost-ONE™ YX400-P Signal Booster**  
**For Sprint® and MetroPCS®**  
**Extending Cell Zones™ for the Home or Office**



Designed for consumers, the zBoost-ONE™ cell phone signal booster extends a Cell Zone™ for 1 – 4 phones/devices on the same PCS carrier (either Sprint or MetroPCS). The zBoost-ONE supports voice and data protocols at 1900MHz in their homes or offices, boosting signal up to 1200 sq. ft. or up to 40 feet from the unit. zBoost-One, the **FIRST ONE PIECE** cell phone signal booster actually **SYNCS to your carrier** to reduce dropped calls and increase call clarity.



**Set-Up is as easy as:**

1. Put unit in window (or wherever you get signal)
2. Plug in power supply
3. Sync to your carrier network by pressing the SyncLink button and making a call
4. Package includes everything you need - zBoost unit (pictured) and power supply (not pictured).

**Benefits include:**

- Increases indoor signal coverage – up to 1200 sq. ft. or 1 - 2 rooms
- No external antennas – ONE PIECE!
- Easy to set up – just put it where you get signal and plug it in
- Supports 1 to 4 users operating on the same carrier network
- Compatible with phones, Smartphone's and data cards using Sprint or MetroPCS
- Extends phone battery life (uses less power when signal is stronger)
- Protects the operator's network using patent-pending technologies

**ZBOOST-ONE FOR ROOM/S IN THE HOME AND OFFICE – PRODUCT SPECIFICATIONS : (YX400-P)**

|                       |   |                          |
|-----------------------|---|--------------------------|
| Frequency             | Uplink<br>1850-1910MHz                  | Downlink<br>1930-1990MHz |
| Networks              | CDMA, 1xRTT, EVDO                       |                          |
| System Gain           | Average 45 dB                           |                          |
| Power Supply          | 90-264 VAC, 50- 60Hz                    |                          |
| Base Unit Weight      | 1.2 lbs.                                |                          |
| Base Unit Size        | 10" x 9" x 3.5" (w x h x d)             |                          |
| Coverage (open areas) | Up to 1200 sq ft or 40 ft from the unit |                          |

Includes multiple patent pending technologies to provide low-cost coverage while continually adapting to signals to prevent interference and remain transparent to the wireless network. Provides an indicator if the antennae are positioned improperly, but will NOT suffer damage or interfere with the Carrier Network.

**For More Information Call 1-877-594-5766 Or visit our website, [www.wpsantennas.com](http://www.wpsantennas.com)**

© 2009 Wi-Ex. All rights reserved.

Sprint and MetroPCS are trademarks of their respective owners.

V. 80609